

RF13.2 - Handset with control



PN (RN): 2022.100.02

The handset can be connected to any of the two audio connectors on the RF13 transceiver or to any transceiver accessory featuring an audio connector. Along with handset functions, it also features transceiver remote control and function mode display. The construction guarantees mechanical resistance, watertightness and stiffness.

Technical parameters

Power supply from the RF13 transceiver or from accessory.

Control functions

- two step volume control, channel selection, start and stop of scanning
- clear override
- selection of displayed information type - channel/frequency
- handset display illumination
- PTT switch
- audio tone signalling

Handset display information

- selective communication
- in the reception and transmission mode displays a symbolic channel number or the frequency
- scanning
- clear override
- in short coded messages mode, it displays a two-digit code of the transmitting station's address and the signal code
- voice encryption mode

Microphone

Microphone sensitivity

Earphone

Earphone sensitivity

Impedance

After pressing the LITE pushbutton the display will be illuminated for

Operating temperature range

Weight

piezoceramic

100 mV (1 kHz/20 mm/80 dB)

electrodynamic loudspeaker

min. 90 dB (900 mV/1 kHz/20 mm)

30 Ω

(10 \pm 3) s

-30 °C to +60 °C

0.4 kg

Set

Handset with control set RF13.2 - (2022.000.02)

Documentation

RF13.2 operating instructions 2022.010.02